


High Voltage Insulation Tester



FR3025E

USER MANUAL

Guangzhou Zhengneng Electronic Technology Co.,Ltd.



CONTENT

I. Safety Rules and Precautions	2
II. Introduction	3
III. Measuring Range and Accuracy	4
IV. Technical Specifications	5
V. Tester Structure	7
VI. Measuring Principle	8
VII. Operation Methods	8
1. Switch On/Off	8
2. Battery Voltage Check	9
3. DC voltage test	9
4. AC voltage test	9
5. Insulation resistance tes	10
6. GUARD Use of protective lines	12
7. Polarization index (PI) and Absorption ratio(DAR)	12
8. Backlight Control	15
9. Alarm Settings	15
10. Data Lock/Storage	15
11. Data Review/Deletion	16
VIII. Battery Replacement	16
IX. Accessories	17

I.Safety Rules and Precautions

Thank you for purchasing our company's digital high-voltage insulation resistance meter. Before you use this instrument for the first time, in order to avoid possible electric shock or personal injury, please be sure to read and strictly observe the safety rules and precautions listed in this manual. .

In any case, the use of this instrument should pay special attention to safety.

- ⊓ The tester is conforming to IEC61010 on design, production and test.
- ⊓ Under any circumstance, it shall pay special attention on safety in use of this tester.
- ⊓ Please don't use high-frequency signal generators like mobile phone and etc. to avoid error during measuring.
- ⊓ Pay attention to words and symbols stick on the Tester.
- ⊓ It shall make sure that tester and accessories are in good condition before use; it can be used only when there is no damaged, naked or broken part in testing wires or insulation layer.
- ⊓ During measurement, it is forbidden to touch bare conductors and circuit under measurement.
- ⊓ Confirm that connector plug of lead has been inserted in the tester interface closely.
- ⊓ Please don't impose over 600V A.C. or D.C. voltage on the part between testing end and interface. Otherwise, it may have damage on the tester.
- ⊓ Please don't measure in an inflammable place. The flame sparkle maybe cause explosion.
- ⊓ During usage of tester, please stop using it when exposed metal is caused by broken enclosure or testing wires.
- ⊓ Please don't keep or store the tester in the spot with high-temperature and moisture, or condensation, and under direct daylight radiation for a long time.
- ⊓ For replacing battery, please confirm testing wire has moved apart the meter, and FUNCTION SWITCH rotary switch is in "OFF" position.
- ⊓ Please put the used batteries in appointed collection place.
- ⊓ When replacing the battery with the meter, make sure that the test line has been removed from the meter and the meter is turned off.
- ⊓ When the meter displays battery low voltage symbol "  ", should replace the battery, otherwise it will lead to ground error.
- ⊓ Do not make measurements when the battery cover is open and during thunder.
- ⊓ Pay attention to measuring range and usage environment stipulated for the Tester.
- ⊓ This measuring device is only to be used, disassembled, adjusted and repaired by qualified personnel with authorization.
- ⊓ When it may cause hazard by continuous use for the reason of the Tester itself, it shall immediately stop using it and deposit it at once, leaving it for disposal by authorized agency.
- ⊓ For risk of danger icon in manual ", users must perform safety operations strictly in compliance with the manual content.

⚠ The instrument output high voltage, please be sure to connect the test line hand to leave the test line before pressing the test button to test, otherwise there is danger of electric shock.

II. Introduction

Digital insulation resistance meter also known as megohmmeter, high voltage insulation resistance tester, etc., for the insulation resistance test. The instrument has a large LCD screen gray backlit display, data storage, data access, alarm, automatic shutdown and other functions. At the same time, it also has the function of measuring AC voltage absorption ratio and polarization index of DC voltage. The machine is beautiful and upscale, has a wide range, high resolution, convenient operation, easy to carry, accurate, reliable, stable performance, strong anti-interference ability. Moreover, it has a shockproof, dustproof, moisture-proof structure and is a commonly used and indispensable instrument for telecommunications, electricity, meteorology, computer rooms, oil fields, electromechanical installation and maintenance, and industrial enterprises that use electricity as industrial power or energy. It is suitable for measuring the resistance value of various insulating materials and the insulation resistance of transformers, motors, cables and electrical equipment.

Digital insulation resistance meter consists of medium and large scale integrated circuits. The output power of the watch is large, and the output voltage level is a lot (with 5 voltage levels). Rated insulation test voltage range 100 ~ 5000V, insulation resistance measurement range 0.01MΩ ~ 200GΩ. DC voltage measurement range 0 ~ 1000V, AC voltage measurement range 0 ~ 750V

III. Measuring Range and Accuracy

Test Function	Output Voltage	Measure Range	Accuracy	Resolution
Insulation Resistance	250V (±10%)	0~10M Ω	±3%rdg ±5dgt	0.01M Ω
		10~100M Ω		0.1M Ω
		100~1000M Ω		1M Ω
		1G~10G Ω		±5%rdg ±5dgt
	500V (±10%)	0~10M Ω	±3%rdg ±5dgt	0.01M Ω
		10~100M Ω		0.1M Ω
		100~1000M Ω		1M Ω
		1G~10G Ω		±5%rdg ±5dgt
	1000V (±10%)	0~20M Ω	±3%rdg ±5dgt	0.01M Ω
		20~200M Ω		0.1M Ω
		200~1000M Ω		1M Ω
		2G~20G Ω		±5%rdg ±5dgt
	2500V (±10%)	0~2000M Ω	±3%rdg ±5dgt	1M Ω
		2000M Ω ~20G Ω	±5%rdg ±5dgt	0.01G Ω
		20G Ω ~200G Ω	±20%rdg ±10dgt	0.1G Ω
	5000V (±10%)	0~2000M Ω	±3%rdg ±5dgt	1M Ω
		2000M Ω ~20G Ω	±5%rdg ±5dgt	0.01G Ω
		20G Ω ~200G Ω	±20%rdg ±10dgt	0.1G Ω

Remark: Common electrical unit conversion

1 T Ω (Tera ohm) =1000G Ω=10¹² Ω

1 G Ω (Giga ohm) =1000M Ω=10⁹ Ω

1 M Ω (Mega ohm) =1000K Ω=10⁶ Ω

Test Function	Measure Range	Accuracy	Resolution
DC Voltage	DC 0.0V~1000V	±1.5%rdg ±3dgt	0.1V
AC Voltage	AC 0.0V~750V	±1.5%rdg ±3dgt	0.1V


IV. Technical Specifications

Function	Insulation resistance test, AC voltage test, DC voltage measurement
Ambient Temperature and Humidity	23°C ±5°C, below 75%rh
Power	DC 9V 6-section LR14 Dry Battery Standby for more than 100 hours
Rated Voltage	250;500;1000;2500;5000
Rated Voltage Accuracy	±10%
Output short-circuit Current	≥2mA
Absorption Ratio Measurement	Have
Polarization Index Measurement	Have
Test Method	DC voltage drop method
Test Voltage	DC voltage measurement
Maximum Capacitive Load	Operates below 1uF
Shift Gear	Automatic shifting
Back light	Controllable gray backlight, suitable for use in dim places
Display Mode	4 large LCD display, gray backlight
Measurement	LED flashes during measurement

Indication	
LCD Size	108mm×65mm
Instrument Size	L/W/H: 240mm×188mm×85mm
Test Line	High pressure rod: red 1 meter Test line: black 1 meter green 1 meter
Measurement Time	Voltage 2 times/sec, insulation resistance 7 seconds/time
Line Voltage	measure below AC600V
Data Storage	500 groups, “MEM” storage instructions, display “FULL” symbol indicates that the storage is full
Data Review	The “MR” symbol indicates when looking up data
Overflow Display	“OL” symbol indicates over-range overflow
Alarm Function	Alarm when the measured value exceeds the alarm setting value
Battery Voltage	Low battery voltage symbol, prompt battery replacement when battery voltage is low
Automatic Shutdown	“APO” Indicate Automatic Shutdown After 15 Minutes
Power Consumption	Standby: About 40mA (backlight off)
	Turn on backlight: about 43mA
	Measurement: about 75mA (backlight off)
Weight	Instrument: 1230g (Including battery)
Working Temperature	-10℃~40℃; Below 80%rh

and Humidity	
Storage Temperature and Humidity	-20°C~60°C; Below 70%rh
Insulation resistance	200MΩ or more (500V between circuit and case)
Pressure Resistance	AC 5160V/rms (Between circuit and case)
Electromagnetic properties	IEC61326 (EMC)
Suitable for Safety Regulations	IEC61010-1 (CAT III 300V、CAT IV 150V、Pollution degree 2);


V. Tester Structure



1. LCD
2. Function Button
3. Test Button
4. Gear Selection Button
5. Test Table Pen
6. High Pressure Test Stick
7. Security Alligator Clip
8. EARTH Ground Interface
9. GUARD protection interface
10. V interface
11. LINE Interface

VI. Measuring Principle

Insulation resistance measurement uses a voltage generator to generate a voltage, V , applied across the resistor, measuring the current I flowing across the resistor, and calculating the ground resistance value R according to the formula $R=V/I$.




$$R = V / I$$

VII. Operation Methods

1. Switch On/Off

Rotate the function selection key to the corresponding position to turn on the power, and turn it to the OFF position to turn it off. After booting, it shows “APO” in the lower right corner. After 15 minutes, it will automatically shut down. After turning off, turn to OFF will restart.

2. Battery Voltage Check

After powering on, if the LCD shows a low battery voltage sign “”, it indicates that the battery is running low. Please replace the battery in time. Sufficient battery power to ensure measurement accuracy

3. DC Voltage Test



When measuring, turn the rotary switch to the gear V_{DC} position, connect the red lead to the V terminal, connect the black lead to the COM, and display the real-time DC voltage. (Figure 1)




Figure 1




Figure 2

4. AC Voltage Test



When measuring, turn the rotary switch to the gear V_{\sim} position, connect the red lead to the V terminal, the black lead to the COM, and the LCD displays the real-time AC voltage value. (Figure 2)

5. Insulation Resistance Test



Insulation resistance test can only be carried out on an uncharged circuit. Before testing, check whether the test circuit wiring is in good condition and whether the circuit under test is energized. If the circuit is live, it may damage the instrument and affect the measurement accuracy.

Must wear high-voltage insulating gloves to operate.

In the insulation resistance range, press the test switch to generate high voltage in the test line head and in the circuit under test. Please be careful to avoid touching.

Be sure to connect the grounding wire (black) to the grounding port of the circuit under test.

Do not touch the circuit immediately after testing. The stored charge may cause electric shock.

Do not remove the test lead immediately. Wait until the discharge is complete before touching the circuit under test.

In order to ensure the measurement accuracy, do not twist the test lines together.


Guaranteed temperature and humidity of the insulation resistance accuracy

Insulation resistance range	Guaranteed the humidity value of the insulation resistance accuracy	Guaranteed temperature of the insulation resistance accuracy
0 Ω-100MΩ	<85% RH (No condensation)	23°C ±5°C
101MΩ-20GΩ	<75% RH (No condensation)	
21GΩ-200GΩ	<65% RH (No condensation)	

Insulation resistance test can only be carried out on an uncharged circuit. Before testing, check that the test leads are good and confirm that the circuit under test is uncharged.


Turn the rotary switch to Ω gear, then press **VSEL** to select the voltage value to be tested.

One end of the ground wire (black) is connected to the instrument connection **EARTH** and the other end is connected to the ground end of the circuit under test. One end of the high-voltage rod test line (red) is connected to the other end of the instrument **LINE** and the head is in contact with the circuit under test. As shown in the figure, press the **TFRT** test button. The LCD shows the measured value. Read the insulation resistance value after the measured value is fixed.



6. GUARD Use of Protective Lines

When the insulation resistance of the cable is measured, the leakage current of the covered surface passes through the interior of the insulator and the current converges, resulting in an error in the insulation resistance value. In order to avoid this phenomenon, as shown in the figure below, use the protection wire (any conductive bare wire) to flow the leakage current through the part. After connecting to the protection port, the leakage current does not flow through the indicator and the insulator can accurately measure the insulation resistance. Please use the protection test cable of the accessory to connect the protection port.



7. Polarization index (PI) and Absorption ratio (DAR)

7.1 The function of Polarization index (PI) and Absorption ratio (DAR):

The Polarization Index (PI) and Absorption Ratio (DAR) are tests to check whether the leakage current of the insulator has increased. The leak current did not increase while confirming the application time. The instrument automatically calculates the polarization index PI and the absorption ratio DAR. As a judgement of the insulation performance, both the polarization index PI and the absorption ratio DAR indicate the change in the insulation resistance over a period of time after the measured object withstands the measured voltage.

7.2 The difference between Polarization index (PI) and Absorption ratio(DAR):

For general insulation tests, such as housing insulation, tool handles, etc. can generally be tested in a relatively short period of time to increase the leakage current with the increase of the voltage application time, so generally can be tested with a short time test, the short-term insulation resistance ratio DAR is called the absorption ratio (see the following formula for the specific test time), but for the large-capacity and long-term absorption process, such as transformers, generators, cables, capacitors and other electrical equipment, sometimes the absorption ratio (DAR) is not enough to reflect the whole process of absorption, and the insulation resistance ratio can be used for a longer time, that is, the ratio between the insulation resistance (R10min) at 10 minutes and the insulation resistance (R1min) at 1 minute describes the entire process of insulation absorption, and PI is called the polarization index.

The PI and DAR values are calculated by the following formula:

$$\text{PI(Polarization index)} = \frac{R10Min}{R1Min}$$

$$\text{DAR(Absorption ratio)} = \frac{R60Sec}{R15Sec}$$

$$\text{DAR(Absorption ratio)} = \frac{R60Sec}{R30Sec}$$

- Remark:**
- 1: R10Min= resistance value measured by the voltage applied for 10 minutes
 - 2: R1Min=R60Sec=the resistance value measured by the voltage applied for 1 minutes
 - 3: R30Sec=It is the resistance value measured by the voltage applied for 30 seconds
 - 4: R15Sec=It is the resistance value measured by the voltage applied for 15 seconds
 - 5: DAR calculation time can choose 15 seconds or 30 seconds

7.3 Polarization index (PI) and Absorption ratio(DAR) Test

The Polarization Index (PI) and Absorption Ratio Test (DAR) can only be performed on uncharged circuits. Before testing, check that the test leads are good and confirm that the circuit under test is charged or not.

Turn the rotary switch to Ω gear, then press VSEL to select the voltage value to test.


Press the **SET** key to set the corresponding mode. The LCD shows “10:01m” as the polarization index mode in the lower left corner of the LCD, “60:15S” as the absorption mode 15 second mode, and “60:30S” as the absorption mode 30 second mode. Small numbers do not show anything for the insulation resistance measurement mode.

One end of the ground wire (black) is connected to the instrument connection **EARTH** and the other end is connected to the ground end of the circuit under test. One end of the high-pressure rod test line (red) is connected to the other end of the instrument **LINE** and the head is in contact with the circuit under test, and the **TFRT** test key is pressed. The LCD displays the measured value. After the measured value is fixed, the absorbance or polarization index can be read.

7.4 Polarization Index (PI) and Absorption Ratio (DAR) Applications:

In engineering, insulation resistance and absorption ratio (or polarization index) can reflect the degree of moisture in the insulation of generators, oil-immersed power transformers and other equipment. The value of the absorption ratio (or polarization index) decreases after the insulation is wet (see Figure 1), so it is an important indicator of whether the insulation is affected by moisture.

It should be pointed out that sometimes the insulation has obvious defects (for example, the insulation breaks down under high pressure), and the absorption ratio or polarization index value is still good. The absorption ratio or polarization index cannot be used to find other local insulation defects other than moisture and dirt.



1-Befor drying,15 degree Celsius; 2-When the end of drying, 73.5 degree Celsius
3-After running 72h, and cooled to 27 degree Celsius

Figure 1 The relationship between the insulation resistance R of a generator and the time t

Polarization Index Reference Judgment Value:

Polarization Index	Above 4	4~2	2.0~1.0	Below 1.0
Judge	The best	Good	Need to pay attention	Bad

Absorption ratio reference judgment value:

Absorption ratio	Above 1.4	1.25~1.0	Below 1.0
Judge	The best	Good	Bad

8. Backlight Control

After power on, press “☀” key to turn the backlight on or off, and the backlight function is suitable for dim places. The default backlight turns off every time you turn it on.

9. Alarm Settings

After power on, long press “☀” to turn on and off the alarm function. Long press “**SET**” key to set the resistance alarm value. Press “▲” or “▼” key to change the current digit size, then press “**SET**” key to save and exit. When the measured voltage value is greater than the alarm critical set value or the insulation resistance value is less than the alarm critical set value and the alarm function is turned on, the instrument flashes the “☹)” symbol and issues a “beep-beep-beep--” alarm sound. The maximum value of the voltage alarm setting is 600V, and the maximum value of the ground resistance alarm setting is 9999MΩ. As shown below:



10. Data Lock/Storage


After the measurement is completed, short press “**HOLD**” key to lock the current display data, and automatically serial storage. If the storage is full, the instrument displays the “**FULL**” symbol. As shown in the following figure: the measured data is 1258mΩ, and the “**HOLD**” display is stored as the third set of data




11. Data Review/Deletion

After booting or measuring, press the "HOLD" button (more than 3 seconds) to enter the data lookup, and store the data read interface "MR" symbol display. Press the "▲" or "▼" key to select the data corresponding to the array number with a step value of 1, press "▲" or "▼" to select the array number with a step value of 10, and press "HOLD" to exit. See below

In the following figure, the number 3 is the current number of groups and 6 is the total number of groups. If there is no stored data, LCD display "NULL", see the figure below.



In the data review state, press and hold the "HOLD" key to enter the data deletion, press "▲" or "▼" to select "NO" or "YES", select "NO" and then press "SET" key to not return to the data review state. "YES" Press "SET" again to delete the stored data. After deletion, the following figure is displayed.



VIII. Battery Replacement

The instrument uses a 9V 6 section LR14 dry battery, when the battery power is reduced, when the voltage drops to 7V, the battery symbol "□" is displayed. Please replace the battery in time. Low voltage affects the measurement accuracy.

IX . Accessories

Instrument	1PC
High pressure rod	1PC (red)
High voltage test line	2 (1 in black, and green)
battery	1.5V alkaline battery 6 section
Manual, warranty certificate	1SET
Instrument box	1PC

The contents of this user manual cannot be used as a reason to use the product for special purposes.

The company is not responsible for other losses caused by use.

The company reserves the right to modify the contents of the user manual. If there is any change, it will not be notified.



GuangZhou ZhengNeng Electronics Technology Co.

Address: 2F, No.15 Baoshu Road, Taihe, Baiyun District, Guangzhou, Guangdong, China

Toll-free call: 4000-1515-38

Tel: 86-20-36544172

Fax: 86-20-37319075

Post: 510540

WebSite: www.znele.com